



	<p><b>Beam detector</b></p> <p><b>Data Sheet</b></p>
<p><b>Product Module</b></p>	<p><b>AW-BK901</b></p>
<p>Operating voltage range</p>	<p>20 V to 28 V DC</p>
<p>Current Parameters</p>	<p>Standby:23mA;Commission:40mA ;Alarm:33mA</p>
<p>Beam Sensor Sensitivity [via Encoder]</p>	<p>Level 1: 2.6 dB;High Sensitivity</p>
	<p>Level 2: 3.4 Medium Sensitivity</p>
	<p>Level 3: 4.8 dB Low Sensitivity</p>
<p>Beam Pathway Length [via Encoder]</p>	<p>Span 1: 8 to 20 meters Short Path</p>
	<p>Span 2: 20 to 40 meters Short Path</p>
	<p>Span 3: 40 to 70 meters Normal Path</p>
	<p>Span 4: 70 to 100 meters Long Path</p>
<p>Beam Path Angle</p>	<p>±0.5°Directional</p>
<p>Alignment Guide</p>	<p>Laser Beam Pointer</p>
<p>Digital Display Guide</p>	<p>Nixie Tube</p>
<p>LED Indicator Guide</p>	<p>Red: Fire ; Yellow: Fault ; Green: Alignment</p>
<p>Reset Time</p>	<p>Less than 2 Second</p>
<p>Relay Capacity [Fire &amp; Fault]</p>	<p>Normally Open/ 2.0 A; 30 VDC</p>
<p>Certificate</p>	 <p><b>C1330a-(cl-7)-01</b></p>